

SPECIFICATIONS **CL30PT2C**


OUTLINES DIMENSIONS

Description

- *Round Type
- *T1 (3mm) Diameter
- *Lens Color: Water Clear
- *With Flange

Features

- *Phototransistor Diode
- *Wide Range of Ic
- *Viewing Angle: 30°
- *Lens for High Sensitivity



Notes:
 1. All Dimensions are in millimeters (inches).
 2. Tolerance is ± 0.25mm (0.01") unless otherwise noted.
 3. Specifications are subject to change without notice.

Part Number	Chip Material	Color of Emission	Lens Type	Viewing Angle
CL30PT2C	Silicon	Phototransistor	Water Clear	30°



ChromeLED Corp. reserves the right to make changes at any time in order to supply the best product possible. The most current version of this document will always be available at: www.chromeled.com

ABSOLUTE MAXIMUM RATINGS
(TA=25°C)

Parameter	Symbol	Max Rating	Unit
Power Dissipation	P _D	100	mW
Emitter-Collector Breakdown Voltage	BV _{ECO}	5	V
Collector-Emitter Sustaining Voltage	V _{CE}	30	V
Relative Humidity at 85C°	HR	85	%
Operating Temperature Range	T _{OPR}	-40~+85	°C
Storage Temperature Range	T _{STG}	-50~+100	°C

I_{FP} = Pulse Width ≤ 10 ms, Duty Ratio ≤ 1/10. Soldering Condition: 260 °C/ 5sec

OPTICAL-ELECTRICAL CHARACTERISTICS
(TA=25°C)





Parameter	Symbol	Test Condition	Value			Unit
			Min	Typ	Max	
Collector-Emitter Sustaining Voltage	V _{CE}	I _C =0.5mA,E=0	30	60	-	V
Collector-Emitter Saturation Voltage	V _{CE(SAT)}	I _C =100uA,E=0.6	-	0.4	-	V
Emitter-Collector Breakdown Voltage	BV _{ECO}	I _C =100uA,E=0	5	7	-	V
Dark Current	I _D	V _{CE} =10V,E=0	-	-	100	nA
Photo Current	I _L	V _{CE} =5V,E=1.0	1.0	6	-	mA
Rise Time	T _R	V _{CC} =5V I _L =800uA R _L =1K OHM	-	10	-	uS
Fall Time	T _F		-	15	-	uS




ChromeLED Corp. reserves the right to make changes at any time in order to supply the best product possible. The most current version of this document will always be available at: www.chromeled.com

OPTICAL CHARACTERISTIC CURVES

PHOTOTRANSISTOR - Typical Electrical / Optical Characteristic Curves



PHOTOTRANSISTOR RELATIVE CURVES



ChromeLED Corp. reserves the right to make changes at any time in order to supply the best product possible. The most current version of this document will always be available at: www.chromeled.com

SOLDERING CONDITIONS – LAMP TYPE LED

* Solder the LED no closer than 3mm from the base of the epoxy bulb. Soldering beyond the base of the tie bar is recommended.

* Recommended soldering conditions

Dip Soldering	
Pre-Heat	100 °C Max
Pre-Heat Time	60 Second Max
Solder Bath Temperature	260 °C Max
Dipping Time	5 Second Max
Dipping Position	No lower than 3mm from the base of the epoxy

Hand Soldering		
	3mm Series	Others
Temperature	300 °C Max	350 °C Max
Soldering Time	3 Second Max	3 Second Max
Position	No closer than 3mm from the base of the epoxy	No closer than 3mm from the base of the epoxy

* Do not apply any stress to the lead. Particularly when heated.

* The LED must not be repositioned after soldering.

* After soldering the LEDs, the epoxy bulb should be protected from mechanical shock or vibration until the LEDs return to room temperature.

* Direct soldering onto a PC board should be avoided. Mechanical stress to the resin may be caused by the PC board warping or from the clinching and cutting of the leadframes. When it is absolutely necessary, the LEDs may be mounted in this fashion, but, the user will assume responsibility for any problems. Direct soldering should only be done after testing has confirmed that no damage, such as wire bond failure or resin deterioration, will occur. LEDs should not be soldered directly to double sided PC boards because the heat will deteriorate the epoxy resin.

* When it is necessary to clamp the LEDs to prevent soldering failure, it is important to minimize the mechanical stress on the LEDs.

* Cut the LED leadframes at room temperature. Cutting the leadframes at high temperature may cause LED failure.



ChromeLED Corp. reserves the right to make changes at any time in order to supply the best product possible. The most current version of this document will always be available at: www.chromeled.com